

# VISTA-10SE

With six zones and 5800 wireless zone expansion, the VISTA-10SE is the industry's most economical and sophisticated panel with light and appliance control.

## **Dependable features to meet your most demanding installations:**

- Six hardwired zones standard
- Expands to 22 total zones when using 5800 wireless
- Seven user codes
- Two-method downloading
- Supports up to four relays
- False alarm prevention features
- Fast and easy E2 programming mode



**Control  
Panel**

## **FEATURES:**

### **End users will appreciate the easy-to-use convenience and control features of the VISTA-10SE:**

- **Wireless Remote Control:** 5804 Four-Button Wireless Key, 5804BDV Bi-Directional Wireless Key with system status feedback or 5804WATCH Four Button Wireless Key
- **Single or Dual Button Wireless Personal Panic:** 5802MN and 5802MN2
- **Home Automation:** Activates lights, appliances, garage doors, and numerous other devices
- **VISTA Interactive Phone Module (VIP):** Gives the end user control of their system from any touchtone phone; the 4286 VIP Module responds in clear English, with over a 100 word vocabulary
- **Full English Display Keypads:** Provides clear understanding of system status and zone locations
- **Paging:** Openings, closings, alarm and trouble messages can be sent directly to a pager, allowing system status to be confirmed; parents can use this feature to verify that their children have arrived home
- **QUICK EXIT:** Enables users to leave the house for a brief time without disarming the system

**ADEMCO  
GROUP**

# VISTA-10SE

## SPECIFICATIONS:

### Electrical

- 500 mA, Aux - 12 VDC
- 16.5 VAC/25 VA transformer
- Alarm output 12 VDC, 2.0 amps max
- For UL installations, combined Aux and alarm output cannot exceed 600mA

### Output Control

- Supports one relay board (part number 4204) for four relays

### Zones

- Six hardwired zones
  - Selectable response: 10msec, 350msec, 750msec
  - Expandable to 22 zones using 5800 wireless
  - 16 zone types to choose from
  - Programmable swinger suppression

### Supported Devices

#### Hardwired Expansion Devices

- 4204 supports up to four relays-15mA standby (each active relay draws an additional 40mA)
- Keypads
  - 6160/6139 Custom English (required for programming) - 150mA/40mA, 100mA/40mA
  - 6150/6128 fixed English LCD - 70mA/40mA, 40mA/20mA
- 4286 VIP Voice Module - 220mA
- Four-wire smoke detectors

### Wireless Receiver Systems

- 5800 receivers
  - 5881ENL up to eight zones - 60mA
  - 5881ENM up to 16 zones - 60mA
- All receivers support
  - Diversity reception with two antennae
  - Remote mounting for best location
  - Unique supervision and low battery indications by point

### Transmitters

- 5800 Series
  - Three-Volt Duracell lithium batteries
  - One mile range
  - Tamper is standard

### Agency Listings

- UL Residential Fire and Burglary and CFM

### Communications

- Touchtone or pulse
- Formats supported
  - ADEMCO Contact ID
  - ADEMCO 4 + 2 Express
  - ADEMCO Low Speed
  - Sescoa/Radionics
- 3 + 1, 4 + 1 and 4 + 2 reporting
- Reporting capabilities: Split, Dual, Split/Dual, Pager

**Control  
Panel**

## ORDERING:

Part No.	Description
VISTA-10SE	Control Panel